



Built in dimensions AIRMATE-8-USB

We have built 2 slightly different models of the AIRMATE-USB.

Before 2013 the front panels did have an edge radius of R=10

After the summer of 2013 the front panels have an edge radius of R=20

If the mixing console needs to be sunk inside furniture the dimensions are: 482x355.15x2mm with a Radius of R=10 or R=20

If the console rest on top of furniture, a hole needs to be made of 452x335mm.

The top panel of the furniture cannot be thicker than 20mm because of the connectors on the backside.

AIRMATE-8-USB:

On top : a hole of 452x325mm in a panel of maximum 20mm.

Milling :482x355.15mm with a radius of R=20 and a depth of 2mm

AIRMATE-12-USB:

On top : a hole of 590x325mm in a panel of maximum 20mm.

Milling :622x355.15mm with a radius of R=20 and a depth of 2mm

Good luck

Feels good does more